

COMMISSION E: Electromagnetic Noise and Interfere (November 2004 – October 2007)

Edited by Ryuji KOGA

Anthropogenic EM Noise and EMC

E.1 2009 International Symposium on EMC, Kyoto

EMC'09/Kyoto is organized by Prof. R. Koga, Okayama University, and will be held in Kyoto at Kyoto International Conference Center, from June 20th to 24th, 2009. This is the sixth EMC Symposium in Japan, because they have been held every five years since 1984. More than 650 people are expected to attend from 20 countries including Japan, and about 250 technical papers will be presented at the Symposium.

E.2 EMC measurement technology

The studies of EMI antenna and electromagnetic field probe calibration method, electromagnetic field probe using electro-optical crystal, EMI suppression effect by ferrite core, measurement method of lightning surge, evaluation method of RF absorber reflectivity in millimeter wavelength, etc, have been performed in this period. Detail descriptions are presented below.

E2-1. Magnetic field probe using magnet-impedance effect

A high frequency carrier type magnetic field probe, which has high sensitivity and high resolution, called GMI (giant magneto-impedance) probe is proposed [Tan, et al., 2005, 2006a, 2006b; Kayano, et al., 2006]. And its validity of magnetic near field measurements is demonstrated by comparing with a conventional shielded loop coil probe and numerical modeling. The GMI probe can clearly detect current concentration at an edge of a microstrip line, which allows high resolution measurements.

E2-2 Antenna factor of EMI measuring antennas

Radio disturbances emitted from electronic equipment have been measured with an EMI antenna, where the disturbance level is expressed in terms of the electrical field strength. In practical measurements, it is given by multiplying the received voltage by the antenna factor of a measuring antenna used. In order to improve the accuracy of the antenna factors in EMI measurement, new antenna calibration methods have been developed:

(1) Application of the non-linear least squares method has been investigated to reduce the uncertainty due to the ground reflection for the conventional EMI antenna calibration in the frequency range from 30 MHz to 300 MHz [Fujii, et al., 2005a]. (2) An antenna calibration technique was proposed using the Standard Antenna Method for vertical polarization. Based on the results of theoretical investigation, appropriate antenna arrangements were found for the calibration of a biconical antenna [Tsushima, et al., 2005]. (3) A new calculable loop antenna having a 180-degree hybrid junction was developed to improve the evaluation accuracy of the generated field strength for the Standard Filed Method. The antenna is also applicable to other calibration methods, such as Standard Antenna Method and Three-Antenna Method [Fujii, et al., 2005b]. (4) A new measurement method of a free space antenna factor was developed using a reverberation chamber [Harima 2005a, 2006, 2007a, 2007b]. (5) Methods for calibrating broadband EMI antennas were investigated [Yamanaka, 2005]

E2-3 Calibration of electromagnetic probe

In order to calibrate an electromagnetic probe up to 18 GHz, a method using open-ended waveguides has been proposed as the standard radiators in the frequency range from 500 MHz to 18 GHz [Ishigami, et al., 2002, 2003a]. A calibration facility was established with an

anechoic chamber. The uncertainty of the facility was evaluated as ± 0.96 dB (500 MHz-8.2 GHz) and ± 1.14 dB (above 8.2 GHz) at the confidence coefficient of 95%, respectively. A TEM cell is also used for the calibration below 500MHz. The uncertainty of the facility was evaluated as ± 0.74 dB at a confidence coefficient of 95%

E2-4 Measurements of EMI suppression characteristics of ferrite cores

A major source of the electromagnetic interference in the frequency range below 1000 MHz is disturbance currents flowing on the cables connected to an electronic device. In order to reduce the noise currents, ferrite cores are usually attached to encircle the cables. However, there is no standard method for measuring the EMI suppression characteristics of the core. Hence, a measurement method for the insertion loss and the reflection coefficients of a ferrite core has been studied and developed [Urabe, et al., 2006a, 2006b].

E. 3 Printed circuit board (PCB) and chip level EMC

EMI control technologies are still of prime interest of high-speed electronic device supplier. Engineers who design electronic apparatuses are always more effective, more versatile method of EMI control. Research activities are held in many farms, but results are apt to be closed to the farm. EMC researches are held in a few universities out of more than 100 Universities that have engineering department.

The studies of simulation of undesired noise form PCB, EMI simulation, EMC design, EMC modeling, Design tools, etc, have been performed in this period. Detail descriptions are presented below.

E3-1 Conducted noise currents from PCB

Conductive noise currents flowing out from vehicle-mounted electronic equipment composed of multi-layer printed circuit boards (PCBs) to wire-harnesses form a major disturbance source for vehicle mounted radios. By using actual vehicle-mounted electronic equipment, it was shown that, to reduce the noise current outflow of this type, combining, not separating, the ground layer patterns of a digital circuit and an analog circuit is more advantageous, while the mechanism remains unknown. Based on an idea that this mechanism generates from a change in the amount of common-mode return currents flowing to the ground, noise current outflows were simulated with the method of moment from three types of simple PCBs having different ground patterns, which were validated from measurement of scattering parameters. Furthermore, it was confirmed that slits on a ground pattern allow conductive noise currents to flow out from PCBs [Maeno, et al., 2006]

Electromagnetic disturbances for vehicle-mounted radios can be caused by conducted noise currents that flow out from electronic equipment for vehicles to wire-harnesses. For reducing the conducted noise currents from electronic equipment for vehicles, a simulation and an experiment were made on how ground patterns affect the noise currents from three-layer printed circuit boards (PCBs) with slit-types and plane-type ground patterns. As a result, it was shown that slits on a ground pattern allow conducted noise currents to flow out from PCBs to wire-harnesses. For the PCBs with plane-type ground and one of three slit-type patterns, on the other hand, both the simulation and examination showed that resonance phenomena occur at unexpected low-frequencies. A circuit analysis revealed that the above phenomena can be caused by the imbalance of a bridge circuit consisting of the trace circuits on the PCB [Maeno, et al., 2007a].

Using actual PCBs in electronic equipment for vehicles, Maeno, et al. investigated whether the grounds of digital and analogue circuits should be combined or separated to reduce the conductive noise current from wire-harness connected to the PCBs. As a result, it was shown

that, in the FM radio frequency band, a ground without separation gives less noise currents and radiated emissions [Maeno, et al., 2007b].

E3-2 Simulation of undesired noise from PCB

In order to explain the undesired electromagnetic radiation from PCB, FDTD modeling of PCB was implemented. Novel FDTD simulation method using multiple-analysis-space was developed [Kasuga, et al., 2005, 2006a, 2006b]. FDTD modeling of the common mode current by a trace placed near the PCB edge was performed [Tanaka, et al., 2005]. It is demonstrated that the common mode current increases as the trace is placed closer to the PCB edge and that a guard band is effective for suppression of the common mode current. These results can serve as design guidelines.

E3-3 Characteristic of EM radiation at Gigahertz Frequency and Its Prediction

It has been demonstrated that a common-mode (CM) current can dominate the EMI processes up to 1GHz, despite the fact that a CM current is smaller than a differential-mode (DM) current. Although the CM current decreases above a few gigahertz, near and far electric fields increase as the frequency becomes higher. It was demonstrated that the DM component should be taken into account for EM radiation at gigahertz frequencies. [Kayano, et al., 2005a, 2005b, 2005c, 2005d]

An equivalent circuit model for predicting EM radiation from a PCB driven by a connected feed cable was proposed and demonstrated [Kayano, et al., 2006]. The equivalent circuit model is based on consideration of concepts of CM antenna impedance and distributed constant circuit to the conventional mechanisms of current- and voltage-driven. The proposed model can predict and explain frequency response of CM current with engineering accuracy, and also express the intermediate state of the current-driven and the voltage-driven.

E3-4 EM Radiation from a PCB with Plural Signal Traces

To provide basic considerations for the realization of methods for predicting the EM radiation from a PCB with plural signal traces driven in the even-mode, the characteristics of the EM radiation resulting from two signal traces on a PCB are investigated experimentally and by numerical modeling [Kayano, et al., 2005, 2006]. The frequency responses in the two signal trace case can be identified using insights gained from the single trace case. Although crosstalk ensues, the rule for PCB design is to keep two high-speed traces on the interior of the PCB whenever possible, from the point of view of EM radiation. An empirical formula to quantify the relationship between the positions of two traces and CM current is provided and discussed by comparing four different models. Results calculated with the empirical formula and FDTD modeling are in good agreement, which indicates the empirical formula may be useful for developing EMI design guidelines.

E3-5 EM Radiation from Interconnected PCBs

To understand the electromagnetic (EM) radiation from interconnected PCBs by a cable, the characteristics of the EM interference of test model PCB are investigated by experiment and numerical modeling [Kayano, et al., 2007a, 2007b]. Comparing the cases with and without the interconnection, the ground plane of the interconnected PCBs and the interconnection cable are dominant radiation factor in the lower frequencies. These factors construct large common-mode antenna. On the other hand, the total EM radiation at GHz frequencies is simply determined by the differential-mode current on the signal trace, and cross-talk current on the victim traces. The DM current on the signal trace can be predicted by transmission line theory.

E3-6 EMI Simulation and EMC design of PCB

Problems to control electromagnetic noise radiated from digital electronic devices have been pursued in the groups of Koga, Inoue, Kami, Kuwabara, Schibuya, and some other. A concise electromagnetic model of the power-bus in a multi-layer PCB has been developed utilizing a cavity-mode model together with the segmentation method. Practical speed was enhanced by 400 times than traditional methods, which is useful as a powerful tool in designing PCBs in terms of turn-around time and scale of computation. Models of electric and magnetic coupling on gapped power bus structures and effects of via inductance on split power/ground planes were also investigated. A method to evaluate common-mode excitation on PCBs was demonstrated with practical PCBs having guard traces. The evaluation model is called “imbalance difference model”. Accuracy of the models has been experimentally examined.

(1) TDR analysis of EM radiation from a bend

Discontinuity such as a bend in a micro-strip line is known as one of major radiation sources. The total radiation from the micro-strip line is, however, being generally investigated because of the difficulties in identifying the radiation from some specific location. In this study, paying attention to the feature of TDR (Time-Domain Reflectometry) measurement, an attempt has been made to extract the radiation only from the bend in a micro-strip line. Such an approach is useful in understanding its radiation mechanism. As a result, it has been founded that the larger the bend angle is, the larger the radiation power becomes. The radiation power achieved 3.5% at maximum when the bending angle was 90° at the frequencies below 1 GHz. (J. Wang and O. Fujiwara, 2005)

(2) Coupling Mechanism of Digital IC

The radiated susceptibility of a microstrip line with a digital IC has been investigated. A circuit approach was used by converting external incident electric and magnetic fields into equivalent current and voltage sources, respectively, and the interference voltages induced at IC pins were simulated by using a circuit simulator. As a result, it has been found that the digital IC exhibits a higher susceptibility for the magnetic field coupling compared to the electric field coupling (J. Wang and K. Kuwabara, 2007).

Resonance in the power-ground plane of PCB is the prime concern when the EM noise is discussed. A novel method to quickly calculate the effect in terms of transfer impedances between separated ports/vias [Wang, et al., 2004, 2005a]. Which was further extended for gapped power bus [Wang et al. 2005b]. Triangular profile of PCB has become possible to treat by it [Wang et al, 206]

E3-7 Modeling of EMC characteristics of digital IC/LSI

The objectives of the EMC modeling of digital circuits are extended to LSIs as noise driving sources, and linear macro-models of LSIs, called LECCS models, have been developed in Prof. Koga's group. Simulation performance of a model for core logic circuits, LECCS-core, and a model for drivers, LECCS-I/O. The LECCS-core model is quite similar to the model ICEM which was proposed by French research group, and collaboration to establish a unified standard model for EMC simulation has been started. The field of research is going into the inside of LSI to estimate the noise current which drives PCB. Increase of frequency range requires this change.

E3-8 Suppression of EM radiation

In order to suppress the undesired electromagnetic radiation from a PCB, new PCB structure and shielding technique are investigated with FDTD modeling and experimentally [Kayano, et al., 2005; Tanaka, et al., 2006]. A guard-band structure as a method for suppressing the EM radiation from a PCB was proposed and demonstrated. A signal trace is located between two ground traces (guard-band: GB). The shield structure is effective for suppressing the CM current at lower frequency. However, structures in which a conductive plate exists near the signal trace yield resonances with high level peak of CM current on near and far-field. On the

other hand, the guard-band structure is more effective than other structures for suppressing the EM radiation in the considered frequency range. Therefore the guard-band will be effective for high-density PCB packaging with high-speed traces.

Confinement of EM noise inside PCB is intended by applying the periodic structures in the power and ground plane, which realizes the band-gap as appears in a crystal. Toyota[2006] has proven its effect.

E. 4 EMC problem related telecommunication system

The studies of telecommunication system using UTP cables, evaluation method of telecommunication system using APD (Amplitude Probability Density), interference caused by microwave oven, EMC evaluation method of UWB system, EMC problems caused by PLC, interference from PCs having dithered clock systems, disturbance for the radio system in LF band, etc, have been performed in this period. Detail descriptions are presented below.

E. 4 EMC problem related telecommunication system

E4-1 APD measurement

Measuring the amplitude probability distribution (APD) of a disturbance has been shown to be a promising method of defining emission limits for protecting digital wireless services. The correlation of disturbance APD to the bit error probability (BEP) of disturbed wireless systems was demonstrated theoretically and experimentally for modulating schemes including spread spectrum [Gotoh, et al., 2005a]. The theory was extended for evaluating the BEP of coded OFDM systems by introducing multichannel APD measurement [Gotoh, et al., 2007a]. A prototype system has been successfully developed realizing real-time measurement of multichannel APD [Gotoh, et al., 2007b]. Theoretical investigation was made on the method and conditions for converting a disturbance APD measured at one frequency to be valid for another frequency [Matsumoto, et al., 2007b]. Application of APD measurement was proposed to the CISPR compliance test of radiated disturbances from microwave ovens [Gotoh, et al., 2005b]. A method was proposed for evaluating the accuracies of APD measuring instruments [Gotoh, et al., 2006].

E4-2 Interference caused by microwave oven noises

Leakage of EM waves from microwave ovens may cause unwanted interference to wireless LAN systems using the 2.4-GHz band. An FM-AM model of oven noise has been developed, and employed to evaluate degradation in the transmission quality of DS-SS (direct sequence spread spectrum) WLAN (wireless LAN) systems interfered with the oven noises [Matsumoto, et al., 2005a]. Band-limited characteristics of oven noise were discussed [Matsumoto, et al., 2005b], and the results were applied to develop a new reduction method of oven interference in DS-SS WLAN systems by means of adaptive filters [Matsumoto, et al., 2005c].

E4-3 UWB (Ultra wide-Band) systems

In order to evaluate peak radiating power from a UWB (ultra wideband) device accurately, a waveform reconstruction method of the electric field emitted by a UWB device was developed based on the time-domain measurement by introducing a compensation technique of waveform distortions caused by the receiving antenna [Ishigami, et al., 2005a]. A measurement system was developed for monitoring electromagnetic field distribution in the UWB frequency band [Ishigami, et al., 2006]. A new method has been proposed and demonstrated for evaluating the interference between the UWB and the wireless LAN by using the GTEM cell [Yamada, et al., 2007].

E4-4 Interference from PCs employing spread spectrum clock systems

Recent electronic devices, such as PCs (personal Computers), usually employ SSC (Spread Spectrum Clock) techniques to reduce the peak spectral amplitude of their radiating clock harmonics by modulating the clock frequency. Measurement was conducted for investigating two-dimensional distribution of frequency modulated noise current on a PC chassis [Marubashi, et al., 2006]. Investigations were made on the effect of the modulating parameters of SSC on the reduction in spectral amplitude of clock harmonics [Matsumoto, et al., 2005d, 2005e, 2006a]. The impact of frequency modulated harmonics on wireless systems was analyzed for Bluetooth [Murakami, et al., 2005, 2006a], MB-OFDM UWB [Murakami, et al., 2006b, 2006c], and OFDM based WLAN [Shimizu, et al., 2005], [Matsumoto, et al., 2006b, 2007a]. It was found that frequency modulated clock harmonics in many cases degraded the transmission performance of such wireless systems more significantly in comparison with unmodulated ones.

E4-5 EMC problem related PLC (Power Line Communication) system

The increase speed of power line communications may affect existing wireless communication system mainly in HF band. To cope with this problem, the effect of buildings on the attenuation in the electric field was investigated by numerical calculation assuming a model of indoor PLC system and typical structures and materials used for buildings in Japan [Ishigami, et al., 2007].

E4-7 Investigation of disturbance for LF band

The Japan Standard Time signal is transmitted at the frequency of 40 kHz and 60 kHz. Electromagnetic disturbances were measured and their statistical properties were investigated in the frequency band [Iwama, et al., 2006, 2007].

E. 5 EMC test facilities

The studies of test methods using rotating electromagnetic fields, correlation between GTEM cells and anechoic chambers, evaluation methods of reverberation chamber, etc, have been performed in this period. Detail descriptions are presented below.

E5-1 Immunity/susceptibility test method

In order to clarify immunity/susceptibility characteristics against radio-frequency electromagnetic fields, a new test method of using electromagnetic fields two-dimensionally rotating at a very low rate was proposed by Prof. Kami's group, which demonstrated the characteristics depicted in visualized three-dimensional map. They also applied the method to a four-septum TEM cell.

E5-2 GTEM Cell

A GTEM (gigahertz transverse electromagnetic) cell is used for immunity and emission tests. The correlation between the immunity-test result in a GTEM cell and that in an anechoic chamber was examined theoretically [Ishigami, et al., 2001, 2003b]. The average electric fields of the EUT surfaces in a GTEM cell and an anechoic chamber were calculated using the FD-TD method in order to evaluate a suitable installation and size of EUT in the GTEM cell. When the size of EUT was 10%, 20%, or 30% of the septum height, the difference in both the test result of the GTEM cell and the anechoic chamber was expected to be about 1dB, 2dB, or 2-3dB, respectively. Moreover, when the EUT surface approached the septum and floor conductor, the difference increased.

E5-3 Reverberation chamber

Statistical properties of the transmission characteristics in a reverberation chamber were analyzed theoretically and experimentally [Harima, 2005b]. The results were applied to developing a new technique to measure the radiating power of wireless devices in a reverberation chamber [Sugiyama, et al., 2005], [Harima, et al., 2005c].

E.6 ESD and system level EMC

The studies of evaluation method of system level EMC, geospace environment simulator, meta-material type RF absorber, etc, have been performed in this period. Detail descriptions are presented below.

E6-1 ESD measurement

The studies on human electrostatic discharges (ESDs) and ESD generators simulating the human ESD, which is being used for standard immunity testing prescribed by the International Electro-technical Commission (IEC), have been conducted in this period by Prof. Fujiwara's group. Detail descriptions are presented below.

(1) Measurement of discharge currents from human ESDs

Discharge currents through a hand-held metal piece from a charged human body were measured with respect to approaching speeds and charge voltages. A circuit approach for calculating the discharge current has also been given. As a result, it was shown that in case of 300 V charge voltage, the current waveform is not affected by the metal piece approaching speed, while in case of 800 V charge voltage, the fast approach gives the higher current peak. These current waveforms can be predicted from the time invariant spark resistance and the measured frequency characteristics of human body impedance seen from a hand-held metal piece [Taka, et al., 2005].

A method was presented for estimating the voltage waveform of a spark from the measured discharge current through a hand-held metal piece from a charged human body, which exhibited the presence of arcs following the spark. In view of the arc and a time-varying resistance based on a spark resistance formula, an improved circuit model was given in order to calculate the discharge current in relation to the charge voltage of a human body [Mori, et al., 2005a].

ESD events due to metal objects electrified with low voltages give a fatal electromagnetic interference to high-tech information equipment. In order to elucidate the mechanism, with a 6-GHz digital oscilloscope, the spark current was measured through a hand-held metal piece from a charged human body, and proposed a current calculation model. Taka, et al. investigated the properties of a spark discharge itself through a hand-held metal piece from a human body electrified with low voltage below 1000 V. From the measured discharge current waveform and the gap voltage calculated from the above-mentioned current calculation model, the gap resistance with respect to time was derived, and the gap length was estimated using a spark resistance formula. As a result, it was shown that for the charge voltage from 200 V to 1000 V, the gap length approximately increases with the charge voltage, while the corresponding gap breakdown field is almost kept constant. The findings were supported by the experimental results that other researchers obtained with their different set-ups consisting of metal electrodes [Taka, et al., 2006a].

The discharge currents due to air discharge through a hand-held metal piece from a charged human-body with respect to charge voltages below 1000 V were measured. The gap breakdown fields were thereby estimated, which were validated from the Paschen's law and other researcher's experimental result [Taka, et al., 2006b].

A method was presented for deriving a gap breakdown field from the measured discharge

current due to collision of a hand-held metal piece from a charged human body. Measurements of the discharge currents were made for charge voltages from 200 V to 1000 V. The corresponding gap breakdown fields were derived, which were validated in comparison with an empirical formula based on the Paschen's law together with other researcher's experimental results [Taka, et al., 2006c].

In IEC 61000-4-2 for electrostatic discharge (ESD) immunity testing, an ESD-gun is used to simulate the ESD events from a charged human body. The gun of this kind injects into a device under test the discharge current through a lumped resistor from a charged lumped capacitor. In actual ESD events from charged human bodies, however, the charge distributed on the body surface is discharged through a spark from the fingertip, and its situation is essentially different from that of the ESD-gun. To understand the behavior of the above-mentioned discharge current, with a 6GHz digital oscilloscope, the discharge current was measured through a hand-held metal piece from a charged human body, and proposed an equivalent circuit model for calculating the discharge current with a time invariant spark resistance. Furthermore, with respect to the approaching speed of the hand-held metal piece, the discharge currents were measured through a metal piece from a human-body with a charge voltage ranging from 200V to 1000V, and estimated the resultant voltage waveforms from the above-mentioned equivalent circuit model. Through these results, in conjunction with the metal piece speed, the dependence on the charge voltage of current peak, current rise time, time-varying spark resistance, spark length and breakdown field was shown. It was confirmed also that the spark resistance value at the current peak time enables one to calculate the discharge current, which supports the validity of the previously proposed circuit model [Mori, et al., 2006a].

It has widely been accepted that ESD events due to charged human bodies with low charge voltages below 1000 V cause a fatal electromagnetic malfunction in high-tech information equipment. In order to understand a mechanism of such human ESD events, with a 12-GHz digital oscilloscope, discharge currents were measured through a hand-held metal bar or a fingertip with an aluminum foil attachment from a charged human body with a charge voltage of 600V, and the effect of the aluminum foil size on discharges through a fingertip was examined. In addition, by using an equivalent circuit previously proposed for calculating the discharge currents, the corresponding discharge voltages, measurement of which is basically impossible, were estimated. As a result, it was shown that the hand-held metal bar and aluminum foil attachment produce a one-shot discharge current with steeply rising time shorter than a hundred picoseconds and the corresponding discharge voltage abruptly changing from the charge voltage to certain remaining voltages due to arcs following sparks, and the peaks of discharge currents through a fingertip increase with the attachment foil size. This suggests that the growth of a spark can be affected mainly by the amount of charges accumulated in the stray capacitances around the fingertip. For the discharge through a fingertip without any aluminum foil attachments, however, the measurement shows that the fingertip produces multiple-shot discharge currents with gently rising time larger than a hundred picoseconds and significantly low amplitudes, which are entirely different from the above cases. This means that the fingertip only could not provide electric energy enough for a spark to grow [Taka, et al., 2007a].

With a 12-GHz digital oscilloscope, discharge currents were measured through a fingertip or a hand-held metal bar from a charged human body with a charge voltage of 600V, and comparison of their discharge waveforms was made in conjunction with the corresponding discharge voltages, which were derived from our previously proposed equivalent circuit model [Taka, et al., 2007b].

A transfer impedance of an SMA receptacle as a wideband measurement electrode being used for discharge currents from a charged human was derived, and its frequency characteristics were measured from 300 kHz to 20 GHz. With a 12-GHz digital oscilloscope, measurement of discharge currents through a hand-held metal bar from a charged human was also made, and thereby the injected currents on the SMA receptacle were reconstructed from

the measured transfer impedance [Kagawa, et al., 2007].

(2) Characteristic measurement of discharge currents from ESD generators

An immunity testing method for ESDs is being specified in IEC 61000-4-2, in which the contact discharge of an ESD-gun is being normally specified. Air discharge testing is known to be a severe immunity test compared to the contact discharge testing, while the discharge current injected is not well reproduced. Grasping the behavior of the current injected by the air discharge would be helpful in establishing the worst-case ESD immunity testing. Mori, et al. previously measured the discharge currents for air discharge testing onto the IEC recommended current transducer with a commercially available ESD-gun, and showed that there exists a specific relationship of $I_p \cdot t_r^\zeta / V_C = \text{constant}$ ($\zeta=0.75$), between rise time t_r and current peak I_p . The current transducer, however, has frequency dependent transfer impedance, which should affect the measured current waveform. Mori, et al. investigated if the above-mentioned specific relationship can be obtained for air discharge of an ESD-gun onto a ground assumed for a metal enclosure of electronic equipment under test. A method was presented for estimating the discharge current from simultaneously measured magnetic fields with two magnetic field probes regardless of the distance between the gun discharge-point and the probe position, which was validated for contact discharge of an ESD-gun to a SMA connector. With this method, the discharge currents injected onto a ground for air discharge testing of an ESD-gun with intentionally fast and slow approaches were estimated. As a result, it was confirmed that there is a specific relationship between rise time t_r and current peak I_p of $I_p \cdot t_r^\zeta / V_C = \text{constant}$ with $\zeta=0.57$ independent of charge voltages and gun approaches [Mori, et al., 2005b].

ESD testing is prescribed in the IEC 61000-4-2, which is conducted by injecting the transient current through contact /air discharge of an ESD-gun. The current calibration in the IEC standard, however, is being made for the contact discharge because the current waveform injected through the air discharge is greatly affected by a gun approaching speed. With two kinds of commercially available ESD-guns, therefore, the transient currents were measured for the air discharge gun with arbitrary approaching speeds. As a result, it was shown that a similar specific relationship holds between the rise-time and current peak for each ESD-gun despite the poor reproducibility of the current waveform, which is also supported by other researcher's finding for the air discharge of a charged metal spheroid [Mori, et al., 2005c].

By testing discharge current of ESD guns on both discharged at contact and in air, their relationship was examined between current peak/rising time and charging voltage. As a result, it was found that the discharge in air had little effect on the discharge current of approaching speed at less than 1 kV, and that it had higher peak and shorter rising time than those of the contact discharge [Mori, et al., 2005d].

According to the IEC 61000-4-2 for ESD immunity testing, an ESD-gun with charge voltages above 2 kV is used to inject a discharge current onto a device under test. The current waveform is prescribed in the IEC standard for contact discharge, but is not specified for air discharge due to its poor reproducibility, although the air discharge gives a severe immunity testing. Furthermore, it is well known that ESD events with low charge voltages below 1 kV cause serious failure to high-tech equipment, while its mechanism remains unknown. In order to clarify the severity of low voltage ESD events, using a 12-GHz digital oscilloscope, current waveforms through air discharge of the ESD-gun with charge voltages from 200V to 1 kV were measured. As a result, it was shown that the current peak and rise time become higher and shorter, respectively, in comparison with those for contact discharge, whose tendency was almost the same as the results for charge voltages below 1 kV previously obtained with a 6-GHz digital oscilloscope. It was also shown that the rise time measured for charge voltages below 500 V reaches the limit of measurement (35 ps) [Mori, et al., 2006b].

By using a 12-GHz digital oscilloscope, discharge currents were measured for air discharge

of an ESD-gun with charge voltages below 1 kV, and demonstrated that the rise time reached the limit of measurement. Based on the Gaussian response of the oscilloscope, the rise time limit was investigated [Mori, et al., 2006c].

Measurements were made in the frequency range from 300kHz to 6GHz of the transfer impedance of a commercially available calibration target used for the immunity testing against ESDs that the IEC prescribes, and thereby the waveforms of discharge currents injected onto the target were reconstructed from their observed output voltages for contact and air discharges of an ESD generator with a charge voltage of 2kV. As a result, it was confirmed that the transfer impedance has an absolute value of almost 1 Ω at frequencies up to 6 GHz, while resonance phenomena were observed at frequencies around 2 and 5 GHz. This result has demonstrated that the reconstructed discharge current waveforms agree well with those of the observed voltages for the contact discharge and air discharge with slow approach, producing the current with a rise time of almost 1 ns, while the reconstructed current has a slightly small peak and gentle rising part in comparison with those of the observed voltage for the air discharge with fast approach, which gives the current within a rapid rise time of a hundred pico-seconds [Taka, et al., 2007c].

E6-2 Equivalent circuit model for human ESD

A circuit approach for calculating the discharge current through a hand-held metal piece from a charged human body has been proposed by Prof. Fujiwara's group. It has been demonstrated that the current waveforms can be predicted from the time variant spark resistance and measured frequency characteristics of the human body impedance [Fujiwara, et al., 2001a, 2003a].

E6-3 ESD contact and air discharge measurement

Measurement was made by Prof. Fujiwara's group for the discharge currents injected onto the Pellegrini target for the contact air discharge of a commercially available ESD-gun with respect to its approaching speed to the target. It was found that the fast approach of the ESD gun provides a sharp current with a steeper rise-time and a higher peak, while the slow approach gives a gentle current with the shorter rise-time but lower peak compared to the case for the contact discharge. It was also found that there exists a specific relationship between the rise-time and the peak current normalized to the charge voltage regardless of the approaching speed of the ESD gun [Fujiwara, et al., 2001b, Fujiwara, et al., 2004].

E6-4 FDTD simulation of contact discharge by an ESD-Gun

The electromagnetic noise caused by an electrostatic discharge (ESD) is a major source of malfunction to high-tech equipment. The ESD testing, therefore, is being specified in the IEC61000-4-2, which prescribes the current waveform from an ESD gun through a IEC recommended current detector (Pellegrini calibration target). This IEC current waveform, however, does not always correspond to the one injected onto an actual device for ESD testing. Prof. Fujiwara's group simulated a contact discharge to ground plates using our previously developed FDTD model of an ESD gun. The induced voltages through a magnetic field probe were simulated when the discharge current was injected directly to the ground plate in contact with an ESD gun, whose results were confirmed with respect to the ground plate sizes experimentally [Fujiwara, et al., 2002, 2003b].

E6-5 Safety evaluation for stochastically varying electromagnetic fields

The cumulative amplitude probability distributions (APD) of leaked electric fields in fusion experimental facilities were measured and an approach to derive their time-average from the measured APD was proposed [Wang, et.al., 2004]. The statistically averaged electric field showed fair agreement with the time-averaged electric field during 6 minutes being specified in

the safety guidelines. This finding suggested the usefulness of the APD measurement in lieu of the field measurement during a 6-minute period because the APD can be obtained for a time period much less than 6 minutes.

E6-6 Geospace environment simulator

In order to make quantitative evaluation of electromagnetic environment around spacecraft, three dimensional electromagnetic particle simulations are being performed using 125 nodes (2 TB Memory) of the Earth Simulator System, reporting various physical processes induced by emission of heavy ions in electric propulsion.

E6-7 Application of meta-material to EM wave absorber and shielding material

Meta-material is the material which can control the dielectric constant and the magnetic permeability. At the special condition, the real part of the dielectric constant and the magnetic permeability are negative. This phenomenon makes the flexibility of a design for EM-absorber and shielding material.

Metamaterial-based EM wave absorbers have been proposed and developed for the use of EMC applications. A new concept of “Equivalent Transformation Methods of Material Constant” (ETMMC) [Kotsuka et al. 2004,2005,2006a,2006b] has been proposed, and “EM-wave absorber based on Integrated Circuit Concept” [Kawamura 2006, Kotsuka 2006c] have been developed. In the course of these researches, new metamaterial EM-wave absorbers have been proposed. These metamaterial EM-wave absorbers are based on the concept of “autonomous control system of living cell” (ACMM) which can change the material constants by computer control [Kotsuka et al. 2006d, 2007a,2007b].

Natural EM Noise

E.7 Lightning

Study in Prof. Kawasaki's group (This section is carried over from the former report)

Thunderstorms observed by TRMM/PR and LIS have been investigated, and Lightning Research Group of Osaka University (LRGOU) has unveiled several interesting features.

Correlation between lightning activities and the snow depth of convective clouds may follow the power-five law. The power five law means that the flash density is a function of the snow-depth to power five. The definition of snow depth is the height of detectable cloud tops by TRMM/PR from the climatological freezing level, and it may be equivalent to the length of the portion where the solid phase precipitation particles exist. This is given by examining more than one million convective clouds, and we conclude that the power five law should be universal from the aspect of the statistic.

Three thunderstorm active areas are well known as “Three World Chimneys”, and those are the Central Africa, Amazon of the South America, and South East Asia. Thunderstorm activities in these areas are expected to contribute to the distribution of thermal energy around the equator to middle latitude regions. Moreover thunderstorm activity in the tropical region is believed to be related with the average temperature of our planet earth. That is why long term monitoring of lightning activity is required. After launching TRMM we have accumulated seven-year LIS observations, and statistics for three world chimneys are obtained. We have recognized the additional lightning active area, and that is around the Maracaibo lake in Venezuela. We conclude that this is because of geographical features of the Maracaibo lake and the continuous easterly trade wind.

Lightning Activity during El Nino period is another interesting subject. LRGOU studies thunderstorm occurrences over west Indonesia and south China, and investigates the influence of El Nino on lightning . We compare the statistics between El Nino and non El Nino periods. We learn that the lightning activity during El Nino period is higher than non El Nino period

instead of less precipitation on the ground during El Nino period. Since we expect the strong correlation between precipitation and lightning activity, the results seem to be against the conventional common sense. However analyzed results for these two areas show no contradictions, or we can say that the results are exactly same from the aspect of statistics. The meteorological comprehension is still remained.

Lightning Research Group of Osaka University (LRGOU) has been working for a novel technique of VHF Broadband Digital Interferometer (BDITF) to monitor thunderstorm activity and to image lightning channels for these ten years. The VHF BDITF has been improved to be a quasi operating system, and LRGOU has equipped the BDITF in Korea, in Australia and at four sites near central Japan. LRGOU controls these BDITFs through internet, and conducts remote and continuous monitoring of lightning activity.

The BDITF antenna is capacitive, which bandwidth is from 25 to 100 MHz including amplifier, and its shape is circular with about 30 cm diameter. The BDITF consists of three antennas, and these antennas are deployed at three apexes of an isosceles right triangle. The length of two sides around the right angle is between 5 to 10 meters, because the antenna spacing is not necessary to be fixed to some required length. These two sides are normally set up to direct to north-to-south and east-to-west. Once we have a lightning flash, a few thousands of VHF impulses are emitted, and the BDITF can detect VHF impulses within about 50 km. The scheme to estimate source location of VHF impulses is based on the Fourier analysis. Received VHF impulses are decomposed into Fourier components by FFT (Fast Fourier Transform). Phase differences for all Fourier components between two antennas output are calculated to estimate the incident angles against the base line of two antennas. Since one unit of BDITF consists of three antennas, two dimensional source locations, azimuth and elevation, can be observed. If we install two sets of BDITF with proper spacing, we are able to have 3-D image of lightning channels.

BDITF observations during winter thunderstorm seasons have been carried out around Mikuni and Kanazawa. Three dimensional images of lightning progressions are observed around Mikuni. The propagation velocity of the negative breakdown is estimated, and it is in the order of ten to power five meters per second. This value is nearly the same of the velocity formally observed by the optical streak camera. The lightning channels with branching are captured, and we learn the excellent capability of BDITF. Possible positively charged region is visualized by detecting negative breakdown during continuing current. The observations around Kanazawa for winter thunderstorms are still ongoing.

An electric field change and VHF/UHF radiation associated with positive cloud-to-ground (CG) flashes during winter in Japan has been observed, and it can be noticed that the intensity of VHF/UHF radiation increases immediately after a return stroke occurrence. It is well known that VHF/UHF radiation intensity by a negative CG decreases during and after a return stroke, and the strong VHF/UHF emission after the return stroke is believed be peculiar to the positive CG. VHF/UHF radiation due to negative CG flashes is emitted from a tip of leader progression, and a lightning channel imaging is available by VHF/UHF interferometer observations. In case of a positive CG, channel imaging of a VHF/UHF interferometer is not available. To interpret the discrepancy of VHF/UHF source mapping between negative and positive CGs, a theory of "Bi-directional Leader Concept" is introduced. That means VHF/UHF radiation associated with a negative breakdown can be observed for both positive and negative CG, and for a negative CG that is the leader progression tip, and for positive CG that is possible positive charge regions. From this aspect, the location of VHF/UHF radiation source for positive CG mapped by interferometers may be equivalent to the location of positive charge distribution inside thunderclouds. In other words we are able to see the charge distribution by the interferometer. The 3D mapping for positive CG obtained during winter thunderstorm in Japan by means of VHF/UHF interferometer frequently gives a very large volume of source distribution, and its horizontal extension occasionally exceeds ten kilometers. The most

possible altitude of the distribution of VHF/UHF source location is equivalent to or slightly lower than the altitude of -10 degree Celsius. The sources are superimposed on the radar cross section, and it is noticed that sources are rather located in a stratified region instead of a convective region. Though it has been believed that the thundercloud during winter in Japan might be small size because of weak convection, our observations by VHF/UHF interferometer are against the conventional understanding. We have occasionally experienced the MCS like thunderclouds even in winter. The total amount of charge is estimated to be a few hundred Coulombs, and it is supposed that thunderclouds, which cause positive CG during winter in Japan, should be a possible parent thundercloud.

E.8 Lightning and spherics

Ionospheric Alfvén Resonances (IARs) as a kind of resonance phenomenon in the ionosphere and magnetosphere, were observed in Kamchatka, Russia ($L = 2.1$) by Hayakawa et al. [2004], who have reported its statistical results on the spectral resonance structures in the ULF/ELF range from 0.1 to 5.0 Hz on the basis of the long-term observation during 2.5 years. Then, Surkov et al. [2006] have presented a theory for mid-latitude IARs excitation due to electromagnetic waves radiated from the lightning discharges, and have found that nearby thunderstorms in a range of 1000 - 2000 km make a main contribution to IARs. The intensity of Schumann resonance, the global electromagnetic oscillations, was monitored at Moshiri, Japan and a good correlation was found between the global ground temperature and the Schumann resonance intensity [Sekiguchi et al., 2006]. Ionospheric DC electric fields and plasma density variations associated meteorological phenomena such as tropical storm and typhoon were investigated [Sorokin et al., 2005].

ELF wave phenomena in the Earth-ionosphere cavity, known as Schumann resonance, have been studied in order to monitor the lower ionosphere and global lightning activity. Ando et al. [2005a] have developed an algorithm to deduce the global lightning activity map as an inverse problem to the ELF data observed at a few stations in the world. Anomalous Schumann resonance effects have been found for earthquakes by Hayakawa et al. [2005a], who have found an anomaly in Schumann resonance (e.g., enhancement in the fourth harmonic etc.) in Japan, in possible association with a large earthquake in Taiwan. They have interpreted that this anomaly is due to the interference between the direct signal from a major lightning source in America and the signal scattered from the Seismo-ionospheric perturbation over Taiwan.

Nickolaenko and Hayakawa [2007] have reviewed the latest works on Schumann resonances and related ELF transient events during the last several years, including ionospheric non-uniformities, the use as a global thermometer, new objects for studies, and new results in old problems.

Nickolaenko et al. [2004] have developed a computer algorithm for accelerating the convergence of the time series computations of the ELF pulsed waveforms propagated in the Earth-ionosphere waveguide.

E.9 Electromagnetic phenomena associated with earthquakes

Seismogenic ULF emissions were detected prior to some large earthquakes; for example, 2004 Niigata-Chuetsu earthquake [Ohta et al., 2005; Hayakawa et al., 2006a] and 2004 Indonesia Sumatra earthquake [Ohta et al., 2007]. Ohta et al. [2005] performed the direction finding from Nakatsugawa, Japan and found that the observed azimuthal directions are consistent with the epicentral directions of both earthquakes, giving a strong evidence on the precursory ULF emissions.

Some sophisticated signal processings were developed and utilized to detect any weak seismogenic ULF emissions [Serita et al., 2005; Hattori et al., 2006; Ida et al., 2006; Ida and

Hayakawa, 2006]. Ida et al. [2006] and Ida and Hayakawa [2006] have applied the fractal (mono- and multi-) analyses to ground-based ULF data to suggest that those fractal analysis are very useful in examining the nonlinear process (self-organized criticality) taking place in the lithosphere.

Hayakawa et al. [2007] have reviewed seismogenic ULF emissions, starting from earlier to the latest results. The most important conclusion from all ULF events reported before, is that there must be a threshold of the possible detection of seismogenic ULF emissions as functions of earthquake magnitude and epicentral distance. Also, the generation mechanisms of ULF emissions (microfracturing, electro-kinetic effects etc.) are also discussed.

Hayakawa [2007] has reviewed the subionospheric VLF/LF propagation during earthquakes, and have presented event and statistical studies on the correlation of ionospheric perturbations as seen by VLF/LF and earthquakes with large magnitudes, say with magnitude larger than 6.0. Also, a few possible mechanisms have been suggested and discussed.

A precursor of ionospheric perturbations to the Sumatra earthquake was found in a subionospheric VLF propagation signal [Horie et al., 2007]. Associated with other large earthquakes, an anomalous effect on Schumann resonance was detected. For one of those earthquakes, the anomaly appeared one week to a few days before the main shock [Hayakawa et al., 2005], and the anomaly was numerically modeled [Nickolaenko et al., 2006]. A subionospheric LF and VLF propagation anomaly caused by ionospheric disturbances [Maekawa et al., 2006; Yamauchi et al., 2007] and anomalous sporadic E layers were observed in prior to earthquakes [Sorokin et al., 2006a]; the effect was numerically modeled [Soloviev et al., 2006]. Various applications of Schumann resonance to ionospheric studies including an earthquake effect were reviewed [Nickolaenko and Hayakawa, 2007]. An electrodynamic model was developed for strong DC electric field formation in the ionosphere above earthquake regions [Sorokin et al., 2006].

References

Adalev, A. S., N. V. Korovkin, M. Hayakawa and J. B. Nitsch[2006], Deembedding and Underterminating Microwave Fixtures with the Genetic Algorithm, *IEEE Trans. Microwave Theory and Techniques*, vol. 54, No.7, 3131-3140, 2006.

Alperovich, L., E. Morozov, M. Hayakawa and K. Hattori[2006], Coherence of the ULF fields in the seismoactive zone of Japan, *Phys. Chem. Earth*, vol. 31, 248-257, 2006.

Ando, Y, P. Maltsev, A. Sukhynyuk, T. Goto, T. Yamauchi, Y. Hobara, M. Sekiguchi, Y. Ikegami, M. Sera, V. Korepanov, and M. Hayakawa[2005a], New ELF observation system at Moshiri, Japan and assessment of Acquired data, *J. Atmos. Electr.*, vol.25, No.1, 29-39, 2005.

Ando, Y. and M. Hayakawa[2006], Recent studies on Schumann resonance, *IEEJ Trans. Fundamentals and Materials*, vol. 126, 1, 28-30, 2006.

Ando, Y. and M. Hayakawa[2006b], Implementation of the perfect matched layer to the CIP method, *IEICE Trans. Electron.*, vol. E89-C, No.5, 645-648, 2006.

Ando, Y., and M. Hayakawa[2007], Use of generalized cross validation for identification of global lightning distribution by using Schumann resonances, *Radio Science*, vol. 42, RS2S16, doi.1029/2006RS003481, 2007.

Ando, Y., M. Hayakawa, A. V. Shvets and A. P. Nickolaenko[2005b], Finite difference analysis of Schumann resonance and reconstruction of lightning discharge, *Radio Sci.*, vol. 40, RS2002, doi:10.1029/2004RS003153, 2005.

Bashkuev, Yu. B., V. B. Khaptanov, M. G. Dembelov, L. Kh. Angarkhaeva, V. P. Boloev and M.

- Hayakawa[2006b], Radioprobing of underground structure of the Failure Gulf, formed as a result of the M7.5 Tsagan earthquake, *Phys. Chem. Earth*, vol. 31, 210-214, 2006.
- Bashkuev, Yu. B., V. P. Melchinov, D. G. Buyanova, L. Kh. Angarkhaeva, M. G. Dembelov, V. B. Khaptanov and M. Hayakawa[2006a], Cryosphere of the earth and its influence on electromagnetic processes in seismoactive mountainous areas, *Phys. Chem. Earth*, vol. 31, 182-188, 2006.
- Biagi, P. F., L. Castellana, T. Maggipinto, G. Maggipinto, A. Minafra, A. Ermini, V. Capozzi, G. Perna, M. Solovieva, A. Rozhnoi, O. A. Molchanov, and M. Hayakawa[2007], Decrease in the electric intensity of VLF/LF radio signals and possible connections, *Natural Hazards Earth System Sci.*, vol. 7, 423-430, 2007.
- Biagi, P. F., L. Castellana, T. Maggipinto, R. Piccolo, A. Minafra, A. Ermini, S. Martellucci, C. Bellecci, G. Perna, V. Capozzi, O. A. Molchanov and M. Hayakawa[2006], LF radio anomalies revealed in Italy by the wavelet analysis: Possible preseismic effects during 1997-1998, *Phys. Chem. Earth*, vol. 31, 403-408, 2006.
- Biagi, P. F., L. Castellana, T. Maggipinto, R. Piccolo, A. Minafra, A. Ermini, S. martellucci, C. Bellecci, G. Perna, V. Capozzi, O. A. Molchanov, and M. Hayakawa[2005], A possible preseismic anomaly in the ground wave of a radio broadcasting (216 kHz) during July-August 1998 (Italy), *Natural Hazards and Earth System Sci.*, vol. 5, 727-732, 2005.
- Bondarenko, A.V., M. Hayakawa, N. V. Korovkin, and E.E. Selina[2005], A general modeling method of synthesis of complex technical and biological system, *Special Issue on Electromagnetic Compatibility, IEEJ, Trans. Fundamentals and Materials*, vol. 125, No.7, 577-582, 2005.
- Bushkuev, Yu. B., I. B. Naguslaeva, Yu. P. Malyshkov, D. G. Buyanova and M. Hayakawa[2006c], Electromagnetic "seismic calm" effect in the Baikal rift zone, *Phys. Chem. Earth*, vol. 31, 336-340, 2006.
- Cervone, G., S. Maekawa, R.P. Singh, M. Hayakawa, M. Kafatos, and A. Shvets[2006], Surface latent heat flux and nighttime LF anomalies prior to the $M_w=8.3$ Tokachi-Oki earthquake, *Natural Hazards Earth System Sci.*, vol. 6, 109-114, 2006.
- Dong, J., Y. Gao and M. Hayakawa[2005], Analysis on subaerial electric field radiated by a unit electric current source in the ground, *Special Issue on Electromagnetic Compatibility, IEEJ, Trans. Fundamentals and Materials*, vol. 125, No.7, 591-595, 2005
- Fedrov, E., A. Ju. Schekotov, O. A. Molchanov, M. Hayakawa, V. V. Surkov and V. A. Gladichev[2006], An energy source for the mid-latitude IAR: World thunderstorm centers, nearby discharges or neutral wind fluctuations?, *Phys. Chem. Earth*, vol. 31, 462-468, 2006.
- Fujii, K., S. Harada, A. Sugiura, Y. Matsumoto, and Y. Yamanaka [2005a], "An Estimation Method for the Free-Space Antenna Factor of VHF EMI Antennas," *IEEE Trans. on EMC*, vol. 47, No. 3, pp. 627- 634.
- Fujii, K., Y. Makajima, Y. Matsumoto, A. Sugiura [2005b], "A Novel Standard Loop Antenna for Antenna Calibration in the MF and HF Bands," 2005 IEEE International EMC Symposium, pp.86-89, Chicago.
- Gotoh, K., S. Ishigami, Y. Matsumoto [2006], "A method for evaluating the accuracies of APD measuring instruments, EMC Europe 2006", pp.723-728, Barcelona.
- Gotoh, K., S. Ishigami, Y. Matsumoto, Y. Yamada and T. Shinozuka [2005b], Utilization of

APD for measurements of radiation from microwave ovens, EMC Europe Workshop 2005, pp. 175-178, Roma.

Gotoh, K., Y. Matsumoto, S. Ishigami, and T. Shinozuka [2007a], "Performance evaluation of multicarrier wireless systems affected by a disturbance using amplitude probability distribution," EMC Europe workshop 2007 Paris.

Gotoh, K., Y. Matsumoto, S. Ishigami, T. Shinozuka, and M. Uchino [2007b], "Development and evaluation of a prototype multichannel APD measuring receiver," 2007 IEEE International EMC Symposium, THPM6SS2, Hawaii.

Gotoh, K., Y. Matsumoto, Y. Yamanaka, and T. Shinozuka [2005a], "APD Measurement for the Disturbance Evaluation Related to the Performance of Digital Communication Systems," IEICE Trans. on Communications, vol. E88-B, No.8 pp.3235-3241.

Guglielmi, A., A. Potapov, B. Tsegmed, M. Hayakawa and B. Dovbnaya[2006], On the earthquake effects in the regime of ionospheric Alfvén resonances, Phys. Chem. Earth, vol. 31, 469-472, 2006.

Guglielmi, A., M. Hayakawa, A. Potapov and B. Tsegmed[2006], Polarization method to detect the co-seismic magnetic oscillations, Phys. Chem. Earth, vol. 31, 299-304, 2006.

Harima [2007a], "Antenna Calibration Using the Reference Antenna Method in a Reverberation Chamber," 2007 European Microwave Week (37th European Microwave Conference), pp. 964-967, Munich.

Harima, K. [2005a], "Determination of EMI Antenna Factor Using Reverberation Chamber," IEEE international EMC Symposium, pp. 93-96, Chicago.

Harima, K. [2005b], "Statistical Characteristics of E-Field Distribution in a Reverberation Chamber," IEICE Trans. on Communications, Vol. E88-B, No. 8, pp. 3127-3132.

Harima K. [2006], "Novel Calibration Technique for EMI Antenna Using Reverberation Chamber," 2006 IEEE International EMC Symposium, Portland.

Harima, K. [2007b], "An Antenna Calibration Technique in Random Electric Fields," 2007 International Symposium on Antenna and Propagation, pp. 919-922, Niigata.

Harima, K. and Y. Yamanaka [2005c], "Determining Total Radiated Power for Short Pulse Signals by Using a Reverberation Chamber," EMC Europe Workshop 2005, pp. 77-79, Rome.

Hattori, K. and M. Hayakawa[2006], Recent progress and state of the art of seismo-electromagnetics, IEEJ Trans. Fundamentals and Materials, Special Issue on Technology 2007: Reviews and Forecasts, vol. 127, 4-6, 2007.

Hattori, K., A. Serita, C. Yoshino, M. Hayakawa and N. Isezaki[2006], Singular spectral analysis and principal component analysis for signal discrimination of ULF geomagnetic data associated with 2000 Izu Island earthquake swarm, Phys. Chem. Earth, vol. 31, 281-291, 2006.

Hayakawa, M, T. Nakamura, D. Iudin, K. Michimoto, T. Suzuki, T. Hanada, and T. Shimura[2005b], On the structure of thunderstorms leading to the generation of sprites and elves: Fractal analysis, J. Geophys. Res., vol. 110, D06104, doi:10.1029/2004JD004545, 2005.

Hayakawa, M. [2006c], Electromagnetic phenomena associated with earthquakes, IEEJ Trans. Fundamentals and Materials, vol. 126, No.4, 211-214, 2006.

Hayakawa, M., and S. F. Timashev[2006e], An attempt to find precursors in the ULF

geomagnetic data by means of flicker noise spectroscopy, *Nonlinear Processes Geophys.*, vol. 13, 255-263, 2006.

Hayakawa, M., A.V. Shvets, and S. Maekawa[2005d], Subionospheric LF monitoring of ionospheric perturbations prior to the Tokachi-oki earthquake and a possible mechanism to lithosphere - ionosphere coupling, *Adv. Polar. Upper Atmos. Res.*, vol. 19, 42-54, 2005.

Hayakawa, M., and K. Ohta[2006b], The importance of direction finding technique for the study of VLF/ELF sferics and whistlers, *IEEJ Trans. Fundamentals and Materials*, vol. 126, No.2, 65-70, 2006.

Hayakawa, M., and O. A. Molchanov[2007c], Seismo-electromagnetics as a new field of radiophysics: Electromagnetic phenomena associated with earthquakes, *Radio Science Bull.*, 320, 8-17, 2007.

Hayakawa, M., D. I. Iudin, E. A. Mareev, and V. Y. Trakhtengerts[2007a], Cellular automaton modeling of mesospheric optical emissions: Sprites, *Physics of Plasmas*, vol. 14, No. 4, pp. 042902 1-6, 2007.

Hayakawa, M., F. Yokose, Y. Ida, and D. Iudin[2006f], Multi-fractal analysis for thunderstorms leading to the generation of sprites and elves, *J. Atmos. Electr.*, 26, No.2, 51-57, 2006.

Hayakawa, M., K. Hattori, and K. Ohta[2007d], Monitoring of ULF (ultra-low-frequency) geomagnetic variations associated with earthquakes, *Sensors*, 7, 1108-1122, 2007.

Hayakawa, M., K. Ohta, A.P. Nickolaenko, and Y. Ando[2005e], Anomalous effect in Schumann resonance phenomena observed in Japan, possibly associated with the Chi-chi earthquake in Taiwan, *Ann. Geophysicae*, vol. 23, 1335-1346, 2005.

Hayakawa, M., K. Ohta, S. Maekawa, T. Yamauchi, Y. Ida, T. Gotoh, N. Yonaiguchi, H. Sasaki and T. Nakamura[2006d], Electromagnetic precursors to the 2004 Mid Niigata Prefecture earthquake, *Phys. Chem. Earth*, vol. 31, 356-364, 2006.

Hayakawa, M., M. Sekiguchi, and A.P. Nickolaenko[2005c], Diurnal variations of electric activity of global thunderstorms deduced from OTD data, *J. Atmos. Electr.*, vol. 25, No.2, 55-68, 2005

Hayakawa, M., M. Sekiguchi, Y. Hobara, and A. P. Nickolaenko[2006g], Intensity of Schumann resonance oscillations and the ground surface temperature, *J. Atmos. Electr.*, 26, No.2, 79-93, 2006.

Hayakawa, M., T. Gotoh, and M. Ikeda[2005a], A network of reception of over-horizon VHF signals associated with earthquakes and some preliminary results, *J. Atmos. Electr.*, Vol.25, No.1, pp. 19-28, 2005.

Hayakawa, M., V. V. Surkov, Y. Fukumoto, and N. Yonaiguchi[2007b], Characteristics of VHF over-horizon signals possibly related to impending earthquakes and a mechanism of seismo-atmospheric perturbations, *J. Atmos. Solar-terr. Phys.*, vol. 69, 1057-1062, 2007.

Hayakawa, M.[2006a], Recent progress in seismo electromagnetics (Electromagnetic phenomena associated with earthquakes), *IEEJ Trans. Fundamentals and Materials*, vol. 126, 1, 43-44, 2006.

Hayakawa, M., T. Suzuki, T. Nakamura, K. Michimoto, and D. Iudin[2007f], Fractal analysis of radar images of Japanese winter thunderclouds inducing sprites and its comparison with their corresponding life cycle, *J. Atmos. Electr.*, vol. 27, 113-121, 2007.

Hayakawa[2007e], M., VLF/LF radio sounding of ionospheric perturbations associated with earthquakes, *Sensors*, 7, 1141-1158, 2007.

Hobara, Y., M. Hayakawa, E. Williams, R. Boldi and E. Downes[2006], Location and electrical properties of sprite-producing lightning from a single ELF site, in "Sprites, Elves and Lightning Discharges", Ed. by M. Fuellekrug, p.211-235, Springer, 2006.

Horie, T., S. Maekawa, T. Yamauchi, and M. Hayakawa[2007], A possible effect of ionospheric perturbations associated with the Sumatra earthquake, as revealed from subionospheric very-low-frequency (VLF) propagation (NWC-Japan), *Int'l J. of Remote Sensing*, 28: 13, 3133-3139, 2007.

Horie, T., T. Yamauchi, M. Yoshida, and M. Hayakawa[2007], The wave-like structures of ionospheric perturbation associated with Sumatra earthquake of 26 December 2004, as revealed from VLF observation in Japan of NWC signals, *J. Atmos. Solar-terr. Phys.*, vol. 69, 1021-1028, 2007.

Ida, Y., and M. Hayakawa[2006], Fractal analysis for the ULF data during the 1993 Guam earthquake to study prefracture criticality, *Nonlinear Processes Geophys.*, vol. 13, 409-412, 2006.

Ida, Y., M. Hayakawa, A. Adaley, and K. Gotoh[2005], Multifractal analysis for the ULF geomagnetic data during the 1993 Guam earthquake, *Nonlinear Processes Geophys.*, vol. 12, 157-162, 2005.

Ida, Y., M. Hayakawa, and K. Gotoh[2006], Multifractal Analysis for the ULF Geomagnetic Data during the Guam Earthquake, *IEEJ Trans. Fundamentals and Materials*, vol. 126, No.4, 215-219, 2006.

Ida, Y., M. Hayakawa, and S. Timashev[2007], Application of different signal analysis methods to the ULF data for the 1993 Guam earthquake, *Natural Hazards Earth System Sci.*, vol. 7, 479-484, 2007.

Ishigami, S., K. Gotoh and Y. Matsumoto [2005a], "Peak power measurement of UWB systems in time domain," *EMC Europe Workshop 2005*, pp. 375-378, Roma.

Ishigami, S., K. Gotoh, Y. Matsumoto [2006], "Development of microwave electromagnetic environment measurement system in the UWB band," *EMC Europe 2006*, pp.802-806, Barcelona.

Ishigami, S., Y. Matsumoto, and K. Gotoh [2007], "Effect of structure and materials of building on electromagnetic fields generated by in-door power line communication systems," *EMC Europe workshop 2007 Paris*.

Iwama, M., T. Shinozuka [2005], "The Environment of Standard Frequency and Time Signal Emission in the LF-Band," *Proc. 2005 International Conference on EMC*, 6A-2, Phuket.

Iwama, M., T. Shinozuka [2006], "The Electromagnetic Environment of Standard Frequency and Time Signal Emission in Japan," *4th Asia Pacific Conference on Environmental Electromagnetics (CEEM 2006)*, pp.268-271, Dalian.

Iwama, M., T. Shinozuka [2007], "The Noise Level and Standard Frequencies in the LF-Band," *The 7th International Symposium on Electromagnetic Compatibility and Electromagnetic Ecology*, pp.228-231, St. Petersburg.

Kagawa, Y., Taka, Y., and Fujiwara, O. [2007], "Transfer Impedance of SMA Receptacle as Wideband Measurement Electrode for Discharge Current from Charged Human," Proceedings of 2007 International China Symposium on Electromagnetic Compatibility, pp. 47-50, Qingdao, China

Kasuga, T. and Hiroshi Inoue [2005]: "Novel FDTD Simulation Method using Multiple-Analysis-Space for Electromagnetic Far Field", IEEE Transaction on Electromagnetic Compatibility, Vol.47, No.2, pp.274-280, May 2005.

Kasuga, T. and Hiroshi Inoue [2006a]: "Elucidation on Characteristics for Electromagnetic Noise Radiation from PCB Using FDTD-MAS Method (Letter)", Trans. of IEICE on Communication, Vol.E89-B, No.3, pp.1030-1032, March 2006 .

Kasuga, T. and Hiroshi Inoue [2006b] : "Simulation and Measurement of Electromagnetic Noise on PCB", 2006 Korea-Japan Joint Conference (KJJC'06), pp.177-180, Sep. 2006.

Kayano Y., Kenji Tan, Kiyoshi Yamakawa, Takashi Komakine and Hiroshi Inoue [2006]:" A Study on Magnetic Field Measurements by a High-Frequency-Carrier Type Magnetic Probe", Proceedings of International Conference on Electronics Packaging (ICEP2006), TA3-8, pp.190-195, April 19-21. 2006.

Kayano, Y., and Hiroshi Inoue [2007b] : "EMI resulting from Interconnected Printed Circuit Boards by a Coaxial Cable", Proceedings of IEEE International Symposium on EMC Symposium (CD-ROM), WE-AM-7-2, 2007-7-11, Hawaii.

Kawamura C., Y. Kotsuka[2006], Broadband EM-Wave Absorber Characteristics Using IC-based Metamaterial, PIERS 06 Proc. P. 380, Aug. 2006.

Kayano, Y., Michiaki Nakano and Hiroshi Inoue [2007a] : "Electromagnetic Radiation Resulting from Printed Circuit Board with Attached Interconnection Cable Driven by Low Voltage Differential Signaling", Proceedings of International Conference on Electronic Packaging (ICEP2007), pp.290-295, Apr. 2007.

Kayano, Y., Motoshi Tanaka and Hiroshi Inoue [2005b]: "Correspondence of Common- and Differential-Mode Components on EM Radiation from Surface Microstrip Line Structure", IEICE Trans. on Electronics, Vol.E88-C, No.8, pp.1688-1695, August 2005.

Kayano, Y., Motoshi Tanaka and Hiroshi Inoue [2005c]:" Radiated Emission from a PCB with an Attached Cable Resulting from a Nonzero Ground Plane Impedance", 2005 IEEE International Symposium on Electromagnetic Compatibility (EMC 2005, Chicago, USA), Proceedings Vol.3, pp.955-960, (11.August 2005).

Kayano, Y., Motoshi Tanaka and Hiroshi Inoue [2006]: "An Equivalent Circuit Model for Predicting EM Radiation from a PCB Driven by a Connected Feed Cable", 2006 IEEE International Symposium on EMC, TUPM0306.pdf, (Portland, USA), Aug. 2006.

Kayano, Y., Motoshi Tanaka and Hiroshi Inoue [2006]: "Electromagnetic radiation resulting from two signal traces on a printed circuit board", IEICE Tans. on Electron., Vol.E89-C, No.8, pp.1217-1223, 2006.

Kayano, Y., Motoshi Tanaka, and Hiroshi Inoue [2005]: "Electromagnetic Radiation Resulting from Plural Signal Traces on a Printed Circuit Board", IEICE 5th International Session on Electro-Mechanical Devices, IS-EMD2005, EMD2005-92, p.75-80. Nov. 2005.

Kayano, Y., Motoshi Tanaka, Hiroshi Inoue [2005d] : "Mechanisms of the Undesired EM

Radiation from a PCB with a Feed Cable", The 5th International Conference on Materials Engineering for Resources (ICMR2005), (Akita, Japan), BP-30, p.485-490. Oct. 2005.

Kayano, Y., Motoshi Tanaka and Hiroshi Inoue [2005]: "PCB Structure with a Guard Band for Suppressing Electromagnetic Radiation", IEICE Trans Communication, Vol.E88-B, No.8, pp.3182-3188, August 2005.

Kayano, Y., Motoshi Tanaka, and Hiroshi Inoue [2005a] : "Characteristics of EM Radiation from a PCB at Gigahertz Frequency", 1st Pan-Pacific EMC Joint Meeting (PPEMC'05), 6, May 2005.

Kopytenko, Yu. A., V. S. Ismaguilov, K. Hattori and M. Hayakawa[2006], Determination of heart position of a forthcoming strong EQ using gradients and phase velocities of ULF geomagnetic disturbances, Phys. Chem. Earth, vol. 31, 292-298, 2006.

Kotsarenko, A., O. Molchanov, M. Hayakawa, S. Koshevaya, V. Grimalsky, R. P?reEnr?quez, and J.A. L?pez Cruz-Abeyro[2005], Investigation of ULF magnetic anomaly during Izu earthquake swarm and Miyakejima volcano eruption at summer 2000, Japan, Natural Hazards Earth System Sci., vol. 5, 63-69, 2005.

Kotsuka Y. [2005], Advanced EM-wave Absorber Technologies, Journal of the IEICE, Vol. 88, No. 12, pp. 932-936, Dec. 2005.

Kotsuka, Y. and C. Kawamura[2006b], Proposal of a New EM-Wave Absorber Based on Integrated Circuit Concept, Vol. J88-C, Trans. of IEICE, No. 12, pp. 1142-1148, Dec. 2005.

Kotsuka, Y. [2004], Electromagnetic Compatibility and Applied Magnetics -----Electromagnetic Wave absorber, Journal of the Magnetics Society of Japan, vol.. 28, No, 11, Nov. 2004.

Kotsuka, Y. [2006b], "A Novel Thin Microwave Absorber Based on the Concept of Equivalent Transformation Method of Material Constant, Proc. of PIERS' 06 , Boston, 2006.

Kotsuka, Y. [2006c], New method of constructing computer controllable metamaterial and its microwave absorber application, in 2006 IEEE MTT-S Int. Microwave Symp. Dig. pp. 927-930, June, 2006.

Kotsuka, Y., C. Kawamura[2007], Novel metamaterial based on the concept of autonomous control system of living cell and its EMC applications, in 2007 IEEE EMC-S Int. EMC Symp. Dig., July, 2007.

Kotsuka, Y., K. Shimodaiara[2006a], A theoretical approach to matching characteristics of anovel absorber based on the concept of equivalent transformation method of material constant," IEICE Trans. Electron.,Vol.E89-C, No. 1, pp. 2-8, Jan., 2006.

Kotsuka, Y., S. Sugiyama, C. Kawamura, K. Murano[2006d], Novel computer control metamaterial beyond conventional configuration and its microwave absorber application, in 2007 IEEE MTT-S Int. Microwave Symp. Dig. June, 2007.

Kushwah, V., V. Singh, B. Singh, and M. Hayakawa[2005], Ultra low frequency (ULF) magnetic field anomalies observed at Agar and their relation to moderate seismic activities in Indian region, J. Atmos. Solar-terr. Phys., vol. 67, 992-1001, 2005.

Maekawa, S., and M. Hayakawa[2006], A Statistical Study on the Dependence of Characteristics of VLF/LF Terminator, IEEJ Trans. Fundamentals and Materials, vol. 126, No.4, 220-226, 2006.

Maekawa, S., T. Horie, T. Yamauchi, T. Sawaya, M. Ishikawa, M. Hayakawa, and H. Sasaki[2006], A statistical study on the effect of earthquakes on the ionosphere, based on the subionospheric LF propagation data in Japan, *Ann. Geophysicae*, 24, 2219-2225, 2006.

Maeno, T., Unou, T. and Fujiwara, O. [2007a], "Reduction of Conductive Noise Currents through Wire-Harnesses from Electronic Equipment for Vehicles," *The IEICE Trans. On Communications*, Vol. J90-B, No. 4, pp. 437-441 (in Japanese).

Maeno, T., Unou, T., Ichikawa, K. and Fujiwara, O. [2006], "Reduction Effect of Ground Patterns on Conductive Noise Currents from Printed Circuit Board," *Proceedings of 2006 Asia-Pacific Microwave Conference*, pp. 59-62, Yokohama, Japan.

Maeno, T., Unou, T., Ichikawa, K. and Fujiwara, O. [2007b], "Effect of Ground Layer Patterns with Slits on Conducted Noise Currents from Printed Circuit Board," *IEEJ Trans. on Electronics, Information and Systems*, Vol. 127, No. 12, pp. 1988-1996 (in Japanese).

Marubashi, M., A. Ogata, K. Fujii, Y. Matsumoto, and A. Sugiura [2006], "Measurement of amplitude and phase of FM noise currents on a personal computer chassis," *4th Asia Pacific Conference on Environmental Electromagnetics (CEEM'2006)*, pp.218-221, Dalian.

Matsudo Yu, T. Suzuki, M. Hayakawa, K. Yamashita, Y. Ando, K. Michimoto, and V. Korepanov[2007], Characteristics of Japanese winter sprites and their parent lightning as estimated by VHF lightning and ELF transients, *J. Atmos. Solar-terr. Phys.*, vol. 69, 1431-1446, 2007.

Matsumoto, Y., K. Fujii and A. Sugiura [2006a], Estimating the Amplitude Reduction of Clock Harmonics due to Frequency Modulation, *IEEE Trans. on EMC*, vol. 48, no. 4, pp. 734-741.

Matsumoto, Y., K. Fujii, A. Sugiura [2005e], "Effects of Spread Spectrum Clocking on Measured Noise Spectra," *EMC Europe Workshop 2005*, pp. 9-12, Roma.

Matsumoto, Y., K. Fujii, and A. Sugiura [2005d], "An analytical method for determining the optimal modulating waveform for dithered clock generation," *IEEE Trans. on EMC*, vol. 47, No.3, pp.577-584.

Matsumoto, Y., K. Gotoh, S. Ishigami, and T. Shinozuka [2007b], "A Method for Estimating Dependence of Disturbance APD on Measurement Frequency," *EMC Europe workshop 2007 Paris*.

Matsumoto, Y., M. Nakatsuka, T. Murakami, K. Fujii, and A. Sugiura [2005c], "Reduction of Microwave Oven Interference in DS-SS WLAN Systems by Using Adaptive Filters," *IEICE Trans. On Communications*, vol. E88-B, No.8, pp.3221-3228.

Matsumoto, Y., M. Takeuchi, K. Fujii, A. Sugiura, and Y. Yamanaka [2005a], "Performance Analysis of Interference Problems Involving DS-SS WLAN Systems and Microwave Ovens," *IEEE Trans. on EMC*, Vol. 47, No.1, pp. 45-53.

Matsumoto, Y., T. Murakami, K. Fujii, and A. Sugiura [2005b], "Band-Limitation Effects on Microwave Oven Noise in the 2.4-GHz Band," *IEICE Trans. on Communications*, vol. E-88B, No.3, pp. 1307-1312.

Matsumoto, Y., T. Shimizu, T. Murakami, K. Fujii, and A. Sugiura [2006b], "Impact of frequency modulated harmonic noises on OFDM-based WLAN systems," *EMC Europe 2006*, pp.817-822, Barcelona.

Matsumoto, Y., T. Shimizu, T. Murakami, K. Fujii, and A. Sugiura [2007a], "Impact of

Frequency-Modulated Harmonic Noises from PCs on OFDM-based WLAN Systems," IEEE Trans. on EMC, vol. 49, no. 2, pp.455-462.

Molchanov, O., A. Rozhnoi, M. Solovieva, O. Akentieva, J. J. Berthelie, M. Parrot, F. Lefeuvre, P. F. Biagi, L. Castellana, and M. Hayakawa[2006], Global diagnostics of the ionospheric perturbations related to the seismic activity using the VLF radio signals collected on the DEMETER satellite, Natural Hazards Earth System Sci., vol. 6, 745-753, 2006.

Molchanov, O., A. Schekotov, M. Solovieva, E. Fedorov, V. Gladyshev, E. Gordeev, V. Chebrov, D. Saltykov, V.I. Sinitsin, K. Hattori, and M. Hayakawa[2005], Near-seismic effects in ULF fields and seismo-acoustic emission: statistics and explanation, Natural Hazards Earth System Sci., vol. 5, 1-10, 2005.

Mori, I., Fujiwara, O. and Ishigami S. [2006b], "Wideband Measurement of Discharge Current Waveform due to Air Discharge of an ESD-gun with Low Charge Voltages," Proceedings of 2006 International Conference on Electrical Contacts, pp. 426-429, Sendai, Japan.

Mori, I., Fujiwara, O., and Ishigami, S. [2006c], "Rise Time Limit of Discharge Current for Air Discharge of an ESD-gun," Proceedings of 2006 Asia-Pacific Conference on Environmental Electromagnetics, pp. 34-37, Dalian, China.

Mori, I., Fujiwara, O., Ishigami, S. and Yamanaka, Y. [2005c], "A Study on Rise-time and Peak of the Transient Current Injected through Air Discharge of an ESD-gun," IEEJ Trans. on Fundamentals and Materials, Vol. 125, No. 7, pp. 598-599.

Mori, I., Taka, Y., and Fujiwara, O. [2005a], "A Circuit Approach to Calculate Discharge Current through Hand-Held Metal Piece from Charged Human-Body," Proceedings of 2005 International Conference on Electromagnetic Compatibility, pp. 4A-4, Phuket, Thailand.

Mori, I., Taka, Y., and Fujiwara, O. [2005b], "Wideband Measurement of Discharge Current Caused by Air Discharge through Hand-Held Metal Piece from Charge Human Body," IEEJ Trans. on Electronics, Information and Systems, Vol. 125, No. 12, pp. 1798-1804 (in Japanese).

Mori, I., Taka, Y., and Fujiwara, O. [2006a], "Wideband Measurement of Discharge Current Caused by Air Discharge through Hand-Held Metal Piece from Charge Human Body," IEEJ Trans. FM, Vol. 126, No. 9, pp. 902-908 (in Japanese).

Mori, I., Taka, Y., Fujiwara, O. and Ishigami, S. [2005d], "Characteristic Comparison of Discharge Currents Caused by Electrostatic Discharge Gun for IEC Immunity Testing," The IEICE Trans. On Communications, Vol. J88-B, No. 12, pp. 2401-2403 (in Japanese).

Murakami, T., Y. Matsumoto, K. Fujii and A. Sugiura [2005], "Interference in the Bluetooth wireless systems caused by electromagnetic disturbances from spread spectrum clock systems," EMC Europe Workshop 2005, pp. 399-402, Roma.

Murakami, T., Y. Matsumoto, K. Fujii and A. Sugiura [2006a], "BER Evaluation of Bluetooth Wireless Systems Disturbed by Radiated Noise of Spread Spectrum Clock System," IEICE Trans. on Communications, vol. E89-B, No. 10, pp. 2897-2904.

Murakami, T., Y. Matsumoto, K. Fujii and A. Sugiura [2006b], "Interference Potential of PC Noises on MB-OFDM UWB Systems," IEEE Communications Letters, vol. 10, no. 12, pp. 804-806.

Murakami, T., Y. Matsumoto, K. Fujii, and A. Sugiura [2006c], "Interference potential of PC noises to ultra wideband communication systems," EMC Europe 2006, pp.807-810, Barcelona.

Nickolaenko A. P., and M. Hayakawa[2007b], Diurnal variations in Schumann resonance intensity in the local and universal times, *J. Atmos. Electr.*, vol. 27, 83-93, 2007.

Nickolaenko, A P., and M. Hayakawa[2007a], Recent studies of Schumann resonance and ELF transients, *J. Atmos. Electr.*, 27, No. 1, 19-39, 2007.

Nickolaenko, A. P., M. Hayakawa and M. Sekiguchi[2006], Variations in global thunderstorm activity inferred from the OTD records, *Geophys. Res. Lett.*, vol.33, L06823, doi:10.1029/2005 GL024884, 2006.

Nickolaenko, A. P., M. Hayakawa, M. Sekiguchi, Y. Ando, and K. Ohta[2006], Model modifications in Schumann resonance intensity caused by a localized ionosphere disturbance over the earthquake epicenter, *Ann. Geophysicae*, 24, 567-575, 2006.

Ohta, K., N. Watahabe, and M. Hayakawa[2007], The obserbation of ultra-low frequency emissions at Nakatsugawa, Japan, in possible association with the Sumatra, Indonesia, earthquake, *Int'l J. of Remote Sensing*, 28: 13, 3121-3131, 2007.

Ohta, K., N. Watanabe and M. Hayakawa[2006], Survey of anomalous Schumann resonance phenomena observed in Japan, in possible association with earthquakes in Taiwan, *Phys. Chem. Earth*, vol. 31, 397-402, 2006.

Ohta, K., N. Watanabe, and M. Hayakawa[2005], The observation of ULF emissions at Nakatsugawa in possible association with the 2004 Mid Niigata Prefecture earthquake, *Earth Planets Space*, vol. 57, 1003-1008, 2005.

Ondoh, T., and M. Hayakawa[2006], Synthetic study of precursory phenomena of the M7.2 Hyogo-ken Nanbu earthquake, *Phys. Chem. Earth*, vol. 31, 378-388, 2006.

Rapoport, Yu. G., O. E. Gotynyan, V. N. Ivchenko, M. Hayakawa, V. V. Grimalsky, S. V. Koshevaya and D. Juares-R. [2006], Modeling electrostatic -photochemistry seismoionospheric coupling in the presence of external currents, *Phys. Chem. Earth*, vol. 31, 437-446, 2006.

Rozhnoi, A. A., M. S. Solovieva, O. A. Molchanov, M. Hayakawa, S. Maekawa and P. F. Biagi[2006], Sensitivity of LF signal to global ionosphere and atomosphere perturbations in the network of stations, *Phys. Chem. Earth*, vol. 31, 409-415, 2006.

Rozhnoi, A. A., M. S. Solovieva, O. A. Molchanov, V. Chebrov, V. Voropaev, M. Hayakawa, S. Maekawa and P. F. Biagi[2006], Preseismic anomaly of LF signal on the wave path Japan-Kamchatka during November-December 2004, *Phys. Chem. Earth*, vol. 31, 422-427, 2006.

Rozhnoi, A. A., M.S. Solovieva, O. A. Molchanov, M. Hayakawa, and P. F. Biagi[2005], Anomalies of LF signal during seismic activity in November-December 2004, *Natural Hazards Earth System Sci.*, vol. 5, 657-660, 2005.

Rozhnoi, A., M. Solovieva, O. Molchanov, P.-F. Biagi, and M. Hayakawa[2007], Observation evidences of atmospheric gravity waves induced by seismic activity from analysis of subionospheric LF signal spectra, *Natural Hazards Earth System Sci.*, vol. 7, 625-628, 2007.

Rozhnoi, A., O. Molchanov, M. Solovieva, V. Gladyshev, O. Akentieva, J. J. Berthelie, M. Parrot, F. Lefeuvre, M. Hayakawa, L. Castellana, and P. F. Biagi[2007], Possible seismo-ionosphere perturbations revealed by VLF signals collected on ground and on a satellite, *Natural Hazards Earth System Sci.*, vol. 7, 617-624, 2007.

Sato, T., Y. Miyazaki, M. Hayakawa and M. Koshihara[2006], Recent trend of electromagnetic theory in advanced technology and society, IEEJ Trans. Fundamentals and Materials, vol. 126, 1, 5-7, 2006.

Schekotov, A. Y., O. A. Molchanov, M. Hayakawa, E. N. Fedorov, V. N. Chebrov, V. I. Sinitsin, E. E. Gordeev, G. G. Belyaev, and N. V. Yagova[2007], ULF/ELF magnetic field variations from atmosphere induced by seismicity, Radio Science, Vol. 42, RS6S90, doi:10.1029/2005RS003441, 2007.

Schekotov, A. Yu., O. A. Molchanov and M. Hayakawa[2006], A study of atmospheric influence from earthquake statistics, Phys. Chem. Earth, vol. 31, 341-345, 2006.

Sekiguchi, M., M. Hayakawa, A. P. Nickolaenko, and Y. Hobara[2006], Evidence on a link between the intensity of Schumann resonance and global surface temperature, Ann. Geophysicae, 24, 1809-1817, 2006.

Serita, A., K. Hattori, C. Yoshino, M. Hayakawa, and N. Isezaki[2005], Principal component analysis and singular spectrum analysis of ULF geomagnetic data associated with earthquakes, Natural Hazards Earth System Sci., vol. 5, 685-689, 2005.

Shekotov, A., O. Molchanov, K. Hattori, E. Fedorov, V. A. Gladyshev, G. G. Belyaev, V. Chebrov, V. Sinitsin, E. Gordeev and M. Hayakawa[2006], Seismo-ionospheric depression of the ULF geomagnetic fluctuations at Kamchatka and Japan, Phys. Chem. Earth, vol. 31, 313-318, 2006.

Shimizu, T., Y. Matsumoto, K. Fujii and A. Sugiura [2005], "Performance evaluation of IEEE802.11a WLAN interfered by spread spectrum noises from a PC clock system," IEEE MAPE2005, pp. 1529-1532, Beijing.

Singh, B., V. Kushwah, V. Singh, M. Tomar and M. Hayakawa[2005], Simultaneous ULF/VLF amplitude anomalies observed during moderate earthquakes in India region, Indian J. Radio and Space Phys., vol. 34, 221-232, August 2005.

Singh, V., B. Singh, M. Kumar and M. Hayakawa[2006], Identification of earthquake sources responsible for subsurface VLF electric field emissions observed at Agra, Phys. Chem. Earth, vol. 31, 325-335, 2006.

Smirnova, N. A., M. Hayakawa[2007], Fractal characteristics of the ground-observed ULF emissions in relation to geomagnetic and seismic activities, J. Atmos. Solar-terr. Phys., vol. 69, 1833-1841, 2007.

Soloviev, O. V., M. Hayakawa and O. A. Molchanov[2006], Seismo-electromagnetic phenomenon in terms of 3D vector problem of subionospheric radio wave propagation across the solar terminator, Phys. Chem. Earth, vol. 31, 428-436, 2006.

Sorokin, V. M., A. K. Yaschenko, and M. Hayakawa[2006], Formation mechanism of the lower-ionospheric disturbances by the atmosphere electric current over a seismic region, J. Atmos. Solar-terr. Phys., vol. 68, 1260-1268, 2006.

Sorokin, V. M., A. K. Yaschenko, and M. Hayakawa[2007a], A perturbation of DC electric field caused by light ion adhesion to aerosols during the growth in seismic-related atmospheric radioactivity, Natural Hazards Earth System Sci., vol. 7, 155-163, 2007.

Sorokin, V. M., A. K. Yaschenko, V. M. Chmyrev and M. Hayakawa[2006a], DC electric field amplification in the mid-latitude ionosphere over seismically active faults, Phys. Chem. Earth, vol. 31, 447-453, 2006.

Sorokin, V. M., A. K. Yaschenko, V. M. Chmyrev and M. Hayakawa[2006b], DC electric field formation in the mid-latitude ionosphere over typhoon and earthquake regions, *Phys. Chem. Earth*, vol. 31, 454-461, 2006.

Sorokin, V. M., A. K. Yaschenko, V. M. Chmyrev, and M. Hayakawa[2005], DC electric field amplification in the mid-latitude ionosphere over seismically active faults, *Natural Hazards Earth System Sci.*, vol. 5, 661-666, 2005.

Sorokin, V. M., A. K. Yashchenko, and M. Hayakawa[2007b], Electric field perturbation caused by an increase in conductivity related to seismicity-induced atmospheric radioactivity growth, *Russian J. Physical Chemistry B*, vol. 1, 644-648, 2007.

Sorokin, V. M., N. V. Isaev, A. K. Yaschenko, V. M. Chmyrev, and M. Hayakawa[2005], Strong DC electric field formation in the low latitude ionosphere over typhoons, *J. Atmos. Solar-Terr. Phys.*, vol. 67, 1269-1279, 2005.

Sugiyama, T., T. Shinozuka, K. Iwasaki [2005], "Estimation of Radiated Power of Radio Transmitters Using a Reverberation Chamber," *IEICE Trans. on Communications*, Vol. E88-B, No. 8, pp. 3158-3163.

Surkov, V. V., and M. Hayakawa[2006], ULF geomagnetic perturbations due to seismic noise produced by rock fracture and crack formation treated as a stochastic process, *Phys. Chem. Earth*, vol. 31, 273-280, 2006.

Surkov, V. V., and M. Hayakawa[2007], ULF electromagnetic noise due to random variations of background atmospheric current and conductivity, *J. Geophys. Res.*, 112, D11116, doi: 10.1029/2006JD007788, 2007.

Surkov, V. V., O. A. Molchanov, M. Hayakawa, and E. N. Federov[2005], Excitation of the ionospheric resonance cavity by thunderstorms, *J. Geophys. Res.*, Vol. 110, A04608, doi: 10.1029/2004JA040850, 2005.

Surkov, V. V., O. A. Pokhotelov, M. Parrot and M. Hayakawa[2006], On the origin of stable IR anomalies detected by satellites above seismo-active regions, *Phys. Chem. Earth*, vol. 31, 164-171, 2006.

Surkov, V. V., M. Hayakawa, A. Y. Schekotov, E. N. Fedorov and O. A. Molchanov[2006], Ionospheric Alfvén resonator excitation due to nearby thunderstorms, *J. Geophys. Res.*, vol. 111, A01303, doi:10.1029/2005JA011320, 2006.

Suzuki Tomoyuki, Masashi Hayakawa, Yu Matsudo, and Koichiro Michimoto[2006], How do winter thundercloud systems generate sprite-inducing lightning in the Hokuriku area of Japan, *Geophys. Res. Lett.*, vol. 33, L10806, doi: 10.1029/2005GL025433, 2006.

Suzuki, T., M. Hayakawa, Y. Hobara, K. Michimoto, and T. Hanada[2006], Characteristics of the sprite parent winter thundercloud with positive single flash in Hokuriku, Japan (A case study on 14th December 2001), *IEEJ Trans. Fundamentals and Materials*, vol. 126, No. 2, 78-83, 2006.

Taka, Y. and Fujiwara, O. [2006b], "Gap Breakdown Field Caused by Air Discharge through Hand-Held Metal Piece from Charged Human-Body," *Proceedings of 2006 Asia-Pacific Conference on Environmental Electromagnetics*, pp. 103-106, Dalian, China.

Taka, Y. and Fujiwara, O. [2006c], "Derivation of breakdown field from discharge current due to collision of hand-held metal piece from charge human body," *Proceedings of 2006 XVI International Conference on Electromagnetic disturbances*, pp. 54-57, Kaunas, Lithuania.

Taka, Y., Adachi, T., Fujiwara, O., Shinobu, I., and Yamanaka, Y. [2007c], "Reconstruction of Discharge Currents Injected on Calibration Target from Electrostatic Discharge Generators," Proceedings of 2007 18th International Zurich Symposium on EMC, pp. 349-352, Munich, Germany.

Taka, Y., Kagawa, Y., and Fujiwara, O. [2007b], "Measurement of Discharge Currents due to Human-ESD," Proceedings of 2007 International China Symposium on Electromagnetic Compatibility, pp. 43-46, Qingdao, China

Taka, Y., Kagawa, Y., and Fujiwara, O. [2007a], "Measurement of Discharge Currents through Fingertip from Charged Human Body," Proceedings of 2007 XVII International Conference on Electromagnetic disturbances, pp. 1.5-1-1.5-4, Bialystok, Poland.

Taka, Y., Mori, I., and Fujiwara, O. [2005], "Measurement of Discharge Current through Hand-Held Metal Piece from Charged Human Body," IEEJ Trans. FM, Vol. 125, No. 7, pp. 600-601.

Taka, Y., Mori, I., and Fujiwara, O. [2006a], "Estimation of Gap Breakdown Field in Contact with Hand-Held Metal Piece from Charged Human Body," Proceedings of 2006 International Conference on Electrical Contacts, pp. 411-414, Sendai, Japan.

Tan K., Takashi Komakine, Kiyoshi Yamakawa, Yoshiki Kayano, Hiroshi Inoue and Masahiro Yamaguchi [2006b], "Detection of High Frequency Magnetic Fields by a GMI Probe", IEEE Transactions on Magnetics, vol.42, no.10, pp.3329-3331, Oct. 2006.

Tan, K., Kiyoshi Yamakawa, Takashi Komakine, Masahiro Yamaguchi, Yoshiki Kayano [2006a], Hiroshi Inoue: "Detection of Wide Band Signal by a High-Frequency-Carrier Type Magnetic Probe", Journal of Applied Physics, Vol.99, No.08B315, pp.08B315-1-08B315-3, June 2006.

Tan, K., Kiyoshi Yamakawa, Takashi Komakine, Masahiro Yamaguchi, Yoshiki Kayano, Hiroshi Inoue [2005]: "Detection of Wide Band Signal by a High-Frequency-Carrier Type Magnetic Probe", Abstract of 50th Conference on Magnetism and Magnetic Materials, AE-06, p.27, October 31, 2005(San Jose, USA).

Tanaka M., Hisashi Takita and Hiroshi Inoue [2006]: "A Study on the Effect of Grounded Conductive Sheet Placed over PCB for Electromagnetic Noise Shielding", Transaction of IEICE on Electronics (Letter), Vol.E89-C, No.1, pp.77-79, January 2006.

Tanaka, M., Yoshiki Kayano, Hiroshi Inoue [2005], "EMI of Printed Circuit Board and Its Modeling", IEICE Transactions on Communications (Japanese Edition), vol.J88-B, no.4, pp.709-717, Apr. 2005.

Todoroki, Y., S. Maekawa, T. Yamauchi, T. Horie, and M. Hayakawa [2007], Solar flare induced D region perturbation in the ionosphere, as revealed from a short-distance VLF propagation path, Geophys. Res. Lett., vol. 34, L03103, doi:10.1029/2006GL028087, 2007.

Toyota, Y., A. E. Engin, T. Kim, M. Swaminathan [2006], Stopband Analysis Using Dispersion Diagram for Two-Dimensional Electromagnetic Bandgap Structures in Printed Circuit Boards, IEEE Microwave and Wireless Components Letters, vol.16, no.12, pp.645-647.

Troyan, V., M. Hayakawa and Yu. Kiselev [2006], Restoration of seismic parameters and electrical conductivity by the diffraction tomography method, Phys. Chem. Earth, vol. 31, 268-272, 2006.

Tsushima, S., K. Fujii, Y. Matsumoto, A. Sugiura, Y. Yamanaka [2005], "Calibration of VHF

EMI antennas using vertical polarization," 2005 International Symposium on antennas and propagation, pp. 1233-1236, Seoul.

Urabe, J., K. Fujii, Armad Mukifza Bin Harun, Y. Matsumoto, and A. Sugiura [2006b], "A Study of EMI Suppression Characteristics of Ferrite Cores," 17th International Zurich Symposium on EMC, pp. 622-625, Singapore.

Urabe, J., K. Fujii, Y. Dowaki, Y. Jito, Y. Matsumoto, and A. Sugiura [2006a], "Measurement Method of the Characteristics of an EMI Suppression Ferrite Core," IEEE Trans. on EMC, vol. 48, no. 4, pp. 774-780.

Wang, J. and K. Kuwabara[2007], "A Study on Radiated Susceptibility of Digital Circuit", Trans. IEICE, vol.J90-B, pp.1213-1215, Nov. 2007.

Wang, J. and O. Fujiwara[2005], "TDR analysis of electromagnetic radiation from a bend of micro-strip line," IEICE Trans. Commun., vol.E88-B, no.8, pp.3207-3212, Aug. 2005

Wang, Z. L. O.Wada, , Y. Toyota, R. Koga[2004], Efficient Calculation of Power Bus Impedance using a Fast Algorithm Together with a Segmentation Method,, IEEJ Trans. FM, Vol.124, No.12, pp.1185-1192.

Wang, Z. L., O. Wada, Y. Toyota, R. Koga[2005a] , Convergence Acceleration and Accuracy Improvement in Power Bus Impedance Calculation with a Fast Algorithm Using Cavity Modes, IEEE Transactions on Electromagnetic Compatibility, Vol.47, No.1 , pp.2-9.

Wang, Z. L., O. Wada, Y. Toyota, R. Koga[2005b], Modeling of Gapped Power Bus Structures for Isolation Using Cavity Modes and Segmentation, IEEE Transactions on Electromagnetic Compatibility, Vol.47, No. 2, pp. 210-218.

Wang, Z. L., O. Wada, Y. Toyota, R. Koga[2006], Virtual Port Parameters in Segmentation Method for Modeling Power Bus Structures in Multilayer PCBs, International Journal of Microwave and Optical Technology, vol.1, no.2, pp.389-393.

Williams, E., R. Boldi, J. Bor, G. Satori, C. Price, E. Greenberg, Y. Takahashi, K. Yamamoto, Y. Matsudo, Y. Hobara, M. Hayakawa, T. Chronis, E. Anagnostou, D. M. Smith, and L. Lopez[2006], Lightning flashes conducive to the production and escape of gamma radiation to space, J. Geophys. Res., vol. 111, D1629, doi:10.1029/2005JD006447, 2006.

Yamada, M., M. Tokuda, S. Ishigami, K. Gotoh, and Y. Matsumoto [2007], "Evaluation of electromagnetic interference between UWB system and wireless LAN using a GTEM cell," 2007 IEEE International EMC Symposium, TUAM44, Hawaii.

Yamanaka, Y., M Sakasai, A. Suzuki, K. Fuji, T. Shinozuka, K. Koike, H. Masuzawa [2005], "Broadband Calibration of EMI Antennas by using Dipole Antennas," Proc. 2005 International Conference on EMC, 3A-2, Phuket.

Yamauchi, T., S. Maekawa, T. Horie, M. Hayakawa, and O. Soloviev[2007], Subionospheric VLF/LF monitoring of ionospheric perturbations for the 2004 Mid-Niigata earthquake and their structure and dynamics, J. Atmos. Solar-terr. Phys., vol. 69, 793-802, 2007.

Yonaiguchi, N., Y. Ida, and M. Hayakawa[2007], On the statistical correlation of over-horizon VHF signals with meteorological radio ducting and seismicity, J. Atmos. Solar-terr. Phys., vol. 69, 661-674, 2007.

Yonaiguchi, N., Y. Ida, M. Hayakawa, and S. Masuda[2007], A comparison of different fractal analyses for VHF electromagnetic emissions and their self-organization for the off-sea

Miyagi-prefecture earthquake, *Natural Hazards Earth System Sci.*, vol. 7, 485-493, 2007.

Yonaiguchi, N., Y. Ida, M. Hayakawa, and S. Masuda[2007], Fractal analysis for VHF electromagnetic noises and the identification of preseismic signature of an earthquake, *J. Atmos. Solar-terr. Phys.*, vol. 69, 1825-1832, 2007.